

Honda GB5000HL 5kVA LPG / Petrol Generator

Prod Code: 5000-G50-26713

Single Phase 3000RPM portable LPG Dual Fuel generator powered by Honda GX270 engine.
Designed and manufactured in the UK by GearGB.

Socket configuration

1x16A 230v 1x16A 115v

You can select the below by clicking the 'choose options' button above:

- Wheel kit (shown in images)
- Electric Start

Please contact us if you wish to include any of the below options:

- 20L fuel tank (shown in dimensional drawing)
- AVR



SPECIFICATIONS	
kVA Output	Small (kVA 0-6)
Sound Level	Industrial
Fuel Type	Petrol / LPG
Starting System	Recoil / Electric
Phase	Single Phase
Generator Type	Fixed Speed
Maximum KVA (@ 0.8pf)	5 kVA
Maximum Output (Watts)	4000
Continuous Output (Watts)	3500
AC Voltage Available	115 / 230
AVR (Automatic Voltage Regulator)	Optional
Frequency (Hertz)	50Hz
Engine Model	Honda GX270
Engine Displacement (cc)	270
Low Level Oil Alert System	Yes
Fuel Tank Capacity (L)	5.3
Transport Wheels	Optional
Lifting Hook	Optional
Approx. Petrol Run Time @ Continuous Output	2H 40M
Approx. Petrol Usage @ Continuous Output (L/H)	1.96
Approx. LPG Usage @ Continuous Output (KG/H)	1.2
Noise Level (1/4 load@7M)	71dBA
Guaranteed noise level (LWA)	96dBA
Length (mm) (With Handles and Wheels)	861
Length (mm) (With Handles Folded out)	1385
Width (mm) (Without Handles and Wheels)	504
Width (mm) (With Handles and Wheels)	693 (Pneumatic wheels 735)
Height (mm) (With Wheels)	718
Height (mm) (Without Wheels)	580
Dry Weight (KG)	59