

Honda GB8000HL 7.5kVA LPG / Petrol Generator

Prod Code: 5000-G50-26714

Single Phase 3000RPM portable LPG Dual Fuel generator powered by Honda GX390 engine.
Designed and manufactured in the UK by GearGB.

Socket configuration

1x32A 230v and 1x16A 230v

You can select the below by clicking the 'choose options' button above:

- Wheel kit (shown in images)
- Electric Start

Please contact us if you wish to include any of the below options:

- 20L fuel tank (shown in dimensional drawing)
- AVR
- 115v ONLY (1x32A 115v and 1x16A 115v)



SPECIFICATIONS		
Model	GB8000HL	
kVA Output	Medium (6-12)	
Sound Level	Industrial	
Fuel Type	Petrol / LPG	
Starting System	Recoil / Electric	
Phase	Single Phase	
Generator Type	Fixed Speed	
Maximum KVA (@ 0.8pf)	7.5kVA	
Maximum Output (Watts)	6000	
Continuous Output (Watts)	5200	
AC Voltage Available	115 or 230	
AVR (Automatic Voltage Regulator)	Optional	
Frequency (Hertz)	50Hz	
Engine Model	Honda GX390	
Engine Displacement (cc)	389	
Low Level Oil Alert System	Yes	
Fuel Tank Capacity (L)	6.2 (Optional 20L)	
Transport Wheels	Optional	
Lifting Hook	Optional	
Approx. Petrol Run Time @ Continuous Output	2H 20M	
Approx. Petrol Usage @ Continuous Output (L/H)	2.7	
Approx. LPG Usage @ Continuous Output (KG/H)	1.8	
Noise Level (1/4 load@7M)	71dBA	
Guaranteed noise level (LWA)	96dBA	
Length (mm) (With Handles and Wheels)	861	
Length (mm) (With Handles Folded out)	1385	
Width (mm) (Without Handles and Wheels)	504	
Width (mm) (With Handles and Wheels)	693 (Pneumatic wheels 735)	
Height (mm) (With Wheels)	718	
Height (mm) (Without Wheels)	580	
Dry Weight (KG)	83	