

Honda GB4000HL 3.75 kVA LPG / Petrol Generator

Prod Code: 5000-G10-26711

Single Phase 3000RPM portable LPG dual fuel generator powered by Honda GX200 engine. Designed and manufactured in the UK by GearGB.

Socket configuration

1x16A 230v and 1x16A 115v

Please contact us if you wish to include any of the options:

- AVR
- 2x16A 115v



SPECIFICATIONS		
Model	GB4000HL	
kVA Output	Small (kVA 0-6)	
Sound Level	Industrial	
LPG	Yes	
Fuel Type	Petrol / LPG	
Starting System	Recoil Start Only	
Phase	Single Phase	
Generator Type	Fixed Speed	
Maximum KVA (@ 0.8pf)	3.75 kVA	
Maximum Output (Watts)	3000	
Continuous Output (Watts)	2600	
AC Voltage Available	115 / 230	
AVR (Automatic Voltage Regulator)	Optional	
Frequency (Hertz)	50Hz	
Engine Model	Honda GX200	
Engine Displacement (cc)	196	
Low Level Oil Alert System	Yes	
Fuel Tank Capacity (L)	3.1	
Approx. Petrol Run Time @ Continuous Output	2H 10M	
Approx. Petrol Usage @ Continuous Output (L/H)	1.45	
Noise Level (1/4 load@7M)	71dBA	
Guaranteed noise level (LWA)	96dBA	
Length (mm) (Without Handles and Wheels)	603	
Width (mm) (Without Handles and Wheels)	413	
Height (mm) (Without Wheels)	433	
Dry Weight (KG)	41	